







Printer DCA (Data Collection Agent) Installation Procedure

Printer DCA Installation


 <p>Printer DCA 4.4.10.30511. msi</p>	<p>Double Click on Printer DCA 4.4.10 located on canon.ca</p>
 <p>Open File - Security Warning</p> <p>Do you want to run this file?</p> <p>Name: C:\Users\U03634\Desktop\Printer DCA 4.4.10.30511.msi Publisher: PrintFleet Inc. Type: Windows Installer Package From: C:\Users\U03634\Desktop\Printer DCA 4.4.10.30511.msi</p> <p><input type="button" value="Run"/> <input type="button" value="Cancel"/></p> <p><input checked="" type="checkbox"/> Always ask before opening this file</p> <p>While files from the Internet can be useful, this file type can potentially harm your computer. Only run software from publishers you trust. What's the risk?</p>	<p>Click Run</p>
 <p>Printer DCA Setup</p> <p>Welcome to the Printer DCA Setup Wizard</p> <p>The Setup Wizard will install Printer DCA on your computer. Click "Next" to continue or "Cancel" to exit the Setup Wizard.</p> <p><input type="button" value=" < Back"/> <input type="button" value=" Next > "/></p>	<p>Click Next</p> <p>The Printer DCA software should be installed on a computer/workstation or a server</p>

	<p>Read the End-User License Agreement (EULA) and check <i>I accept the terms in the License Agreement</i>.</p> <p>Click <i>Next</i>.</p>
	<p>By default the Printer DCA will be install under C:\Program Files\Printer DCA\ or C:\Program Files (x86)\Printer DCA\ If you want to change the location click on the <i>Browse</i> button.</p> <p>Click <i>Next</i>.</p>




You are now ready to install the first part of the Printer DCA.

Click **Install**




You have now completed the installation of the Printer DCA.

Click **Finish**







You will be presented with the EULA once again. You will have the option to print a copy of the EULA.


Click **Accept**



You now arrive at the Printer DCA Setup Wizard. You are able to select the language you wish the Setup Interface to be in.

Click **Next**.


 <p>Canon Canada Inc. Canon - Automated Meter Read Program - DCA PIN # PrintFleet to: Sent by:</p> <hr/> <p>Good morning, Here is the Server Name and your PIN Code. Server: <code>bsdmeter.canon.ca</code> PIN Code: ABCD-1234</p> <p>If you have any questions or require any assistance, please do not hesitate to contact us, thank you.</p>  <p>Because It Counts Pour tout ce qui compte</p> <p>Program d'Automatisation de Lecture de Compteur Automated Meter Read Program Canon Canada Inc. 8801 Trans-Canada Highway, Saint-Laurent, Québec H4S 1Z6 canon.ca/lecturedecompteurs canon.ca/gratuitiel canon.ca/meterread canon.ca/freeware PrintFleet@canada.canon.com T 1-866-226-6634 Option 4, Option 2 F 1-866-342-0377</p> <p>Join us on Facebook: www.facebook.com/CanonCanada</p>	<p>Within 24 to 48 hours you should receive an e-mail from PrintFleet@canada.canon.com with the Server Name and your PIN Code to activate your Printer DCA.</p> <p>To reopen the Printer DCA Setup go to: Start>All Programs>Printer DCA>Printer DCA</p>						
 <p>Printer DCA - Setup Wizard</p> <p>Printer DCA Activation</p> <p>Please key in your activation information. Once you are finished, click next to continue. To configure a proxy server, click "Show Proxy Configuration" in the lower right corner.</p> <p>Server: <input type="text"/> PIN Code: <input type="text"/></p> <p>Show Proxy Configuration</p> <p>Step 1 of 4 < Back Next ></p>	<p>To activate the Printer DCA you will need to indicate the following.</p> <p>Server Name: <i>bsdmeter.canon.ca</i></p> <p>PIN Code: Provided in the e-mail from PrintFleet@canada.canon.com.</p> <p>Click Next.</p>						
 <p>Printer DCA - Setup Wizard</p> <p>Scan Settings</p> <p>The following scan ranges have been pre-configured to match your network settings. You can edit these ranges after the setup is complete by opening the Printer DCA and navigating to the "Scan" tab.</p> <p>Scan Ranges:</p> <table border="1"><tr><td>10.124.121.1-10.124.121.254</td></tr><tr><td>10.124.169.1-10.124.169.254</td></tr><tr><td>10.124.17.1-10.124.17.254</td></tr><tr><td>10.124.2.1-10.124.2.254</td></tr><tr><td>10.124.25.1-10.124.25.254</td></tr><tr><td>10.124.5.1-10.124.5.254</td></tr></table> <p>Step 2 of 4 < Back Next ></p>	10.124.121.1-10.124.121.254	10.124.169.1-10.124.169.254	10.124.17.1-10.124.17.254	10.124.2.1-10.124.2.254	10.124.25.1-10.124.25.254	10.124.5.1-10.124.5.254	<p>Once the Printer DCA is Activated it will display a pre-configured scan range. You can modify your Scan Range in the from the Scan Tab (General)</p> <p>Click Next.</p>
10.124.121.1-10.124.121.254							
10.124.169.1-10.124.169.254							
10.124.17.1-10.124.17.254							
10.124.2.1-10.124.2.254							
10.124.25.1-10.124.25.254							
10.124.5.1-10.124.5.254							



Ensure that **Allow Intelligent Updates** is checked that way your Printer DCA is always up to date and functioning.

Ensure that **Enable Remote Configuration** is NOT checked off


Click **Next**.



The Setup of your Printer DCA has now been completed. Ensure that **Open the Printer DCA Interface** is checked so you can ensure all settings are correct and adjust any settings that need to be modified.

You will also want **Start the Print DCA Service** to be checked so that the Printer DCA start communicating with the Server.

Click **Finish**.




On the Printer DCA Interface you can change the language. Simply go to:

Options > Language >

You can then select the language you want from the dropdown list.


Available Languages are:

- Deutsch (Deutschland)
- English (United States)
- español (España)
- français (France)



Status Tab


The first screen that appears when you open the Pinter DCA Interface is the **Status** tab.



Communication Tab

The **Communication** tab provides information on the Server in which the Printer DCA is communicating to.


In the event you are using a Proxy server you will be able to configure the Printer DCA so that it recognizes Printers on the Proxy server



Scan Tab (General)


The *Scan (General)* tab is where you configure the network range you want the Printer DCA to scan. You are able to specify multiple IP Ranges as well as individual IP Addresses. You can also indicate a specified IP Address you want to exclude.

Please modify the Scan Interval from 60 to 960 minutes and click on **Save**



Scan Tab (Advanced)


The *Scan (Advance)* tab is where you can configure the Printer DCA to run an Focus Scan (extra scan) at a specific time to scan your entire network to discover new equipment



File Viewer Tab

The File Viewer tab allows you to open the Log File from a specific date. Additionally you are able to open the archive file. Finally, you can specify the amount of time you want to keep the log and archive files.

This screen will be useful for any troubleshooting that may be required as you can access source information from a single location.



When you do any changes to the Printer DCA Interface ensure that you save the changes you have made.

You are also able to do a **Force Scan** which allows you to perform a Printer DCA Scan before the next interval.

Should you encounter any issue or require any assistance during the Printer DCA installation please contact Canon Business Solutions Division at 1-866-226-6634 Option 2, Option 4 followed by Option 2 or via e-mail at PrintFleet@canada.canon.com.