

EOS WEBCAM UTILITY SOFTWARE

Mac OS Official Release Version

With so many of us relying on livestreaming and video calls on a day-to-day basis to stay connected with friends, visiting clients, getting an education, and so much more, the quality of that connection is key. We are proud to announce the release of the official version of our EOS Webcam Utility software for Mac OS, which lets you turn your compatible Canon EOS camera into your main webcam using only a USB cable.

REQUIREMENTS

- ✓ A camera compatible with EOS Webcam Utility Official Release software (see chart below).
- ✓ A USB cable* to connect the camera to the computer.
- ✓ A computer with an internet connection and an operating system capable of running the EOS Webcam Utility Release software.
- ✓ EOS Webcam Utility Beta version needs to be uninstalled if previously installed on the computer.

The following are current system requirements: macOS Catalina (10.15), macOS Mojave (10.14) or macOS High Sierra (10.13), Intel Based Processor, 2GB RAM or greater, display screen resolution of 1,024x768 pixels or more, and approx. 32,000 colors or more.



**See compatible accessory chart on the last page*

ENHANCEMENTS

- ✓ More compatibility with your favorite communication and streaming programs.
- ✓ A larger list of compatible cameras that can take advantage of the EOS Webcam Utility.
- ✓ The ability to record internally on your camera while you are streaming giving you the maximum image quality for post-production editing.*

**Recording time might not be the same as streaming time, refer to your manual for maximum recording time*

COMPATIBLE APPLICATIONS



EOS Webcam Utility software does not support apps downloaded from the App Store. Please download the application from the service provider's website where available.

Subscription to a third party service required. Subject to third party service providers terms and conditions.

Neither Canon Inc. nor Canon U.S.A., Inc. represents or warrant any third-party product or feature referenced hereunder.

All referenced product names and marks are trademarks of their owners and are hereby acknowledged.

MAC OS VERSION COMPATIBILITY

Application	macOS® Catalina (10.15)	macOS® Mojave (10.14)	macOS® High Sierra (10.13)
Apple Facetime			
Cisco Webex®	Native app: No Browser: Yes (Chrome)	Native app: No Browser: Yes (Chrome)	
Discord	Native app: No Browser: Yes (Chrome)	Native app: No Browser: Yes (Chrome)	
Facebook Live			
Hangouts™			
Hangouts Meet™			
Messenger			
Microsoft Teams	Native app: No Browser: Yes (Chrome)	Native app: No Browser: Yes (Chrome)	
Open Broadcaster Software®			
Skype	Native app: No Browser: Yes (Chrome)	Native app: No Browser: Yes (Chrome)	
Slack	Native app: No Browser: Yes (Chrome)	Native app: No Browser: Yes (Chrome)	Native app: No Browser: Yes (Chrome)
Streamlabs			
YouTube Live			
ZOOM			

COMPATIBLE CAMERAS

Note: Genuine Canon accessories are recommended - see chart on last page for more information

EOS Cameras

EOS-1D X Mark III	EOS RP **	EOS Rebel SL3 **
EOS-1D X Mark II	EOS 7D Mark II	EOS Rebel SL2 **
EOS-1D X *	EOS 7D *	EOS Rebel SL1 *
EOS-1D C *	EOS 90D **	EOS Rebel T7 **
EOS 5DS R	EOS 80D **	EOS Rebel T6
EOS 5DS	EOS 77D **	EOS Rebel T5 *
EOS R5 *	EOS 70D *	EOS Rebel T3 *
EOS 5D Mark IV	EOS 60D *	EOS Rebel T100 **
EOS 5D Mark III *	EOS Rebel T8i * **	EOS M6 Mark II **
EOS R6 * **	EOS Rebel T7i **	EOS M50 **
EOS R	EOS Rebel T6s *	EOS M50 Mark II * **
EOS Ra *	EOS Rebel T6i	EOS M200 **
EOS 6D Mark II **	EOS Rebel T5i *	
EOS 6D *	EOS Rebel T3i *	

PowerShot Cameras


PowerShot G5X Mark II **	PowerShot G7X Mark III **	PowerShot SX70HS **
--------------------------	---------------------------	---------------------

* Recently added camera


** Camera does not ship with a bundled USB interface cable

HOW TO DOWNLOAD


1. Open your web browser and either go directly to our [EOS Webcam Utility Website](#) OR follow the steps below to navigate through the [Canon USA Website](#).




2. If navigating through the Canon USA Website, at the top of the main page, find the "Search Area"



3. Type "EOS Webcam Utility" in the "Search Area" and hit enter.



4. Select your camera model from the list displayed. You will then be redirected to the download page.




5. Select and download “EOS Webcam Utility” under the software section.
Note: If the beta version is installed, the official version will replace it.

The screenshot shows the Canon website for the EOS RP camera. The top navigation bar includes the Canon logo, links for EXPLORE, PRODUCTS, LEARN, SUPPORT, ABOUT, and SHOP, and a search bar. The main content area features a large image of the EOS RP camera with a red circular badge stating 'FIRMWARE UPDATE NOW AVAILABLE!'. Below the camera image are navigation arrows and buttons for 'VIEW MORE DETAILS' and 'FIND A DEALER'. To the right of the camera image, there are buttons for 'DRIVERS & DOWNLOADS', 'MANUALS', and 'NEED SERVICE?'. Below these buttons, there is contact support information for Canon USA, including a phone number and a website link. A red button labeled 'REGISTER PRODUCT' is also visible. Below the camera image, there is a section titled 'EOS RP' with a grid of links for Specifications, Wireless Help, Drivers & Downloads, Manuals, FAQs, Product Advisories, Warranty, and Software Development Kit (SDK). Below this grid, there is a section titled 'Drivers & Downloads' with a table showing the operating system (macOS High Sierra v10.13 (Detected)) and the language (English). The table has columns for Software, Firmware, Utilities, and SDK. The 'Software' column is highlighted in red. Below the table, there is a section titled 'Optional Software' with a table showing the file name (EOS Webcam Utility 1.0 for macOS), the date (1/1/20), and the file size. A red button labeled 'SELECT' is located at the bottom right of the table.


File Name	Date	File Size
EOS Webcam Utility 1.0 for macOS	1/1/20	

HOW TO INSTALL


6. Once the software download is complete, locate the “EOS Webcam Installation Package” in your computer’s “Downloads” folder. The file will be called “EOSWebcamUtility-MAC1.0.pkg.zip”. Double-click the .zip file.




7. Run the EOSWebcamUtility-MAC1.0.pkg file.




8. You will then be greeted by the "Introduction" screen. Click "Continue."




9. Read through the Important Information, then click "Continue"




10. Read through the Software License Agreement and if you agree, click "Continue" then "Agree"




11. Select your folder destination, then, click "Continue."




12. The installer is now ready to begin. Click "Install" to proceed.



- 13.** The installer will alert you that the computer must be restarted after installation. Click "Continue Installation" to proceed.



- 14.** Close other applications and click "Restart" to restart your computer.



HOW TO SETUP


- 15.** Once restarted, using your USB cable, connect one end of the USB cable to your camera, and then connect the other end to your computer. A direct connection to the computer is recommended.

Note: See the compatible accessory chart at the end regarding finding the correct cable for your camera.



- 16.** Set your camera to [Movie Mode]. Use your camera's Mode Dial, Mode Switch or Mode Button interface.


Note: Optimal settings are a resolution of [Full-HD] and a frame rate of [29.97P] (30P). If your camera doesn't have a [29.97P] (30P) setting, selecting [23.98P] (24P) will also work.



17. Lastly, open your web conferencing/streaming app of choice. Find the [Audio/video settings] menu and set "EOS Webcam Utility" as the camera of choice. Confirm that your computer's built-in microphone is selected as your "microphone"

Note: Audio is not transmitted from the camera.



Camera



Enjoy easy-to-use, high-quality video conferencing with EOS Webcam Utility functionality.

For troubleshooting and the latest information on support for EOS Webcam Utility, please visit the Canon Forum Support thread: canon.us/forum-eoswebcamutility

EOS WEBCAM UTILITY STATUS SCREENS

Status Screen	Meaning	Action
	Please check your USB cable connection.	<ol style="list-style-type: none">1. Please check that your camera's USB cable is properly connected both at the camera-side and at the computer side.2. Check your battery or power adapter3. Check that your camera is powered on
	The camera's LiveView video signal is being utilized by another application.	<p>Please [Exit], and [Close] any applications that may be running on your computer, or in your task tray that may be connected to your camera, or using the camera's LiveView video signal.</p> <p>For example: EOS Utility or an application connected to the camera.</p>

COMPATIBLE ACCESSORIES

Note: Genuine Canon accessories are recommended.

Camera	USB Cable	AC Power Supply
EOS-1D X Mark III	IFC-100U (to USB C) (bundled)	AC Adapter AC-E19 with DC Coupler DR-E19
EOS-1D X Mark II	IFC-150U II (bundled)	AC Adapter AC-E19 with DC Coupler DR-E19
EOS-1D X	IFC-200U (bundled)	ACK-E4
EOS-1D C	IFC-200U (bundled)	ACK-E4
EOS 5DS R	IFC-150U II (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 5DS	IFC-150U II (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS R5	IFC-100U (to USB C) (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 5D Mark IV	IFC-150U II (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 5D Mark III	IFC-150U II (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS R6**	IFC-100U (to USB C)**	AC Adapter AC-E6N with DC Coupler DR-E6
EOS R	IFC-100U (to USB C) (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS Ra	IFC-100U (to USB C) (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 6D Mark II**	IFC-400PCU**	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 6D	IFC-200U (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS RP**	IFC-100U (to USB C)**	AC Adapter AC-E6N with DC Coupler DR-E18
EOS 7D Mark II	IFC-150U II (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 7D	IFC-200U (bundled)	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 90D**	IFC-600PCU**	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 80D**	IFC-400PCU**	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 77D**	IFC-400PCU**	AC Adapter AC-E6N with DC Coupler DR-E18
EOS 70D	IFC-400PCU (bundled) or IFC-200U	AC Adapter AC-E6N with DC Coupler DR-E6
EOS 60D	IFC-130U (bundled) or IFC-200U	AC Adapter AC-E6N with DC Coupler DR-E6
EOS Rebel T8i**	IFC-600PCU*	AC Adapter AC-E6N with DC Coupler DR-E18
EOS Rebel T7i**	IFC-400PCU*	AC Adapter AC-E6N with DC Coupler DR-E18
EOS Rebel T6s	IFC-130U(bundled) or IFC-200U	AC Adapter AC-E6N with DC Coupler DR-E18
EOS Rebel T6i	IFC-130U(bundled) or IFC-200U	AC Adapter AC-E6N with DC Coupler DR-E18
EOS Rebel T5i	IFC-130U(bundled) or IFC-200U	Compact Power Adapter CA-PS700 with DC Coupler DR-E8
EOS Rebel T3i	IFC-130U(bundled) or IFC-200U	Compact Power Adapter CA-PS700 with DC Coupler DR-E8
EOS Rebel SL3**	IFC-600PCU**	AC Adapter AC-E6N with DC Coupler DR-E18
EOS Rebel SL2**	IFC-400PCU**	AC Adapter AC-E6N with DC Coupler DR-E18
EOS Rebel SL1	IFC-130U(bundled) or IFC-200U	Compact Power Adapter CA-PS700 with DC Coupler DR-E15
EOS Rebel T7**	IFC-400PCU**	Compact Power Adapter CA-PS700 with DC Coupler DR-E10
EOS Rebel T6	IFC-130U(bundled) or IFC-200U	Compact Power Adapter CA-PS700 with DC Coupler DR-E10
EOS Rebel T5	IFC-130U(bundled) or IFC-200U	Compact Power Adapter CA-PS700 with DC Coupler DR-E10
EOS Rebel T3	IFC-130U(bundled) or IFC-200U	Compact Power Adapter CA-PS700 with DC Coupler DR-E10
EOS Rebel T100**	IFC-400PCU**	N/A
EOS M6 Mark II**	IFC-100U (to USB C)*	Compact Power Adapter CA-PS700 with DC Coupler DR-E17
EOS M50**	IFC-600PCU**	Compact Power Adapter CA-PS700 with DC Coupler DR-E12
EOS M50 Mark II**	IFC-600PCU**	Compact Power Adapter CA-PS700 with DC Coupler DR-E12
EOS M200**	IFC-600PCU**	Compact Power Adapter CA-PS700 with DC Coupler DR-E12
PowerShot G5 X Mark II**	IFC-100U (to USB C)**	N/A (Note: USB Power Adapter PD-E1 cannot be used at the same time as USB Interface Cable)
PowerShot G7 X Mark III**	IFC-100U (to USB C)**	N/A (Note: USB Power Adapter PD-E1 cannot be used at the same time as USB Interface Cable)
PowerShot SX70 HS**	IFC-600PCU**	N/A

** Camera does not ship with a bundled USB interface cable.